

3G MOBILE SETTING



CREATE THREE ACCESS POINTS FOR 3G SERVICE SURFING:

1. 3G WAP SETTING

1. Press **Menu** **▶ Select Tools ▶ Settings ▶ Connection ▶ Select Access Points**
2. Press **Options** **▶ Select New Access Point:**
 - **Connection Name:** Mfone WAP
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** Mfone
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** <Leave default>
3. Press **Options** **▶ Select Advanced Settings:**
 - **Network Type:** <Leave default>
 - **Phone IP Address:** <Leave default>
 - **DNS Address:** <Leave default>
 - **Proxy Server Address:** 172.16.203.85
 - **Proxy Port Number:** 8080

2. INTERNET WEB SURFING & 3G BASIC SERVICE

- A. Press **Menu** **▶ Select Tools ▶ Settings ▶ Connection ▶ Select Access Points**
- B. Press **Options** **▶ Select New Access Points**
 - **Connection Name:** Mfone INTERNET
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** Mfone
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** <Leave default>

3. MMS SETTING

1. Go to **Menu** **▶ Select Tools ▶ Settings ▶ Connection ▶ Access Points**
2. Press **Options** **▶ Select New Access Point:**
 - **Connection Name:** Mfone MMS
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** <Leave default>
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** http://172.16.205.10:38090
3. Press **Options** **▶ Select Advanced Settings:**
 - **Network Type:** <Leave default>
 - **Phone IP Address:** <Leave default>
 - **DNS Address:** <Leave default>
 - **Proxy Server Address:** 172.16.203.85
 - **Proxy Port Number:** 8080

E-MAIL CONFIGURATION



1. Go to **Menu** **▶ Select Message**
2. Press **Options** **▶ Settings ▶ E-mail ▶ Open Mailboxes**
(If you use this function first time, it will prompt: "No mailbox defined. Define now". Follow the guide to define a new mailbox) **Options ▶ New mailbox**
3. Select mail type as **IMAP4** or **POP3** (select **POP3**)
 - **My e-mail address:** <Your email address>
 - **Incoming mail server:**
<Your incoming mail server name>
 - **Outgoing mail server:**
<Your ISP outgoing server name>
 - **Access point in use:** Select Mfone INTERNET
 - **Mailbox name:** <Your mail box name> [Ex: mymail]

3. Back to **Mailboxes** **▶ Select mymail ▶ Press Options ▶ Select Connection Settings:**

1. Incoming E-mail:

User name: <Your e-mail ID>
Password: <Your e-mail password>
Incoming mail server: <Your incoming mail server name> (if defined, leave default)
Access point in use: Select Mfone INTERNET (if defined, leave default)
Mailbox name: <Your mailbox name>
Mailbox Type: POP3
Security (ports): <Leave default>
Port: <Leave default>
APOPsecure login: <Leave default>

2. Outgoing E-mail:

My e-mail address: <Your e-mail address>

(if defined, leave default)

User name: <Your e-mail ID>
Password: <Your e-mail Password>
Outgoing mail server: <Your ISP outgoing server name> (if defined, leave default)
Access point in use: Mfone INTERNET (if defined, leave default)
Security (ports): <Leave default>
Port: <Leave default>

▶ Select User settings:

- **My name:** Your name
- **Send message:** <Leave default>
- **Send copy to self:** <Leave default>
- **Include signature:** <Leave default>
- **New e-mail alerts:** <Leave default>

MMS CONFIG.



1. Press **Menu** **▶ Select Messages**
2. Press **Options** **▶ Select Settings ▶ Select Multimedia messages**
 - **Image size:** <Leave default>
 - **MMS creation mode:** <Leave default>
 - **Access point in use:** Mfone MMS
 - **Multimedia retrieval:** <Leave default or Always automatic>
 - **Allow anon.msgs:** <Leave default>
 - **Receive adverts:** <Leave default>
 - **Deny report sending:** <Leave default>
 - **Message validity:** <Leave default>

VIDEO STREAM CONFIG.



1. Press **Menu** **▶ Select Application ▶ Select Realplayer ▶ Press Options ▶ Select Settings ▶ Select and open Streaming:**
 - **Proxy:** <Leave default> **▶ Select Network:**
 - **Default Access Point:** Mfone INTERNET
 - **Online Time:** <Leave default>
 - **Lowest UDP Port:** <Leave default>
 - **Highest UDP Port:** <Leave default>
2. Press **Menu** **▶ Select Web**
3. Press **Options** **▶ Navigation Options ▶ Select Go to web address**
4. Input the Video Stream address you want to see (Such as <http://172.16.206.16:8080/testportal.html>).
 - Press **Go to** **▶ Select Access point:** Mfone INTERNET

3G WAP/WEB BROWSING



1. Press **Menu** **▶ Select Web**
2. Press **Options** **▶ Select Navigation options ▶ Select Go to web address**
3. Input the WAP address you want to browse (such as <http://www.waplinks.com>) **▶ Press Go to ▶ Select Access point:** Mfone WAP
4. Input the Web address you want to browse (such as <http://www.yahoo.com>) **▶ Press Go to ▶ Select Access point:** Mfone INTERNET